

# Mega Single



## ▼ Photometrics

8ft Single	FC	185	77	41	25	17	12
	Feet	2	4	6	8	10	12
6ft Single	FC	160	60	30	18	12	8
	Feet	2	4	6	8	10	12

8ft Single	LUX	2465	1089	603	379	259	188
	Meters	0.5	1	1.5	2	2.5	3
6ft Single	LUX	2164	867	452	272	182	130
	Meters	0.5	1	1.5	2	2.5	3

## ▼ Fixture Specifications

Fixture	Lamp	Lamp Type	Dimensions	Weight w/ Lamp
8ft Mega Single	1	F120/T12	97 x 4.5 x 3.5" w/ 3.5" barndoors (246.5 x 11.5 x 9cm w/ 9cm barndoors)	6.8 lb (3.1kg)
6ft Mega Single	1	F100/T12	73.5 x 4.5 x 3.5" w/ 3.5" barndoors (186.5 x 11.5 x 9cm w/ 9cm barndoors)	6.3 lb (2.8kg)

## ▼ Ballast Specifications

Ballast	Input Voltage	Output Frequency	Amperage	Lamp Switch	Output Switch	Dimensions	Weight
Mega Single	120VAC 50/60Hz	25kHz	F120/2.0A, F100/1.8A	1-Off	HO/Std	11 x 2.5 x 2.5" (28 x 6.5 x 6.5cm)	2.1 lb (0.9kg)
Mega Single	230VAC 50/60Hz	25kHz	F120/1.2A, F100/0.9A	1-Off	HO/Std	10.5 x 4 x 2.5" (26.5 x 10 x 6.5cm)	2.7 lb (1.2kg)

## ▼ Details



The 8ft and 6ft Mega Single portable lighting systems can be seen most often as built-in set design lights for feature film, commercial production and music videos. The Mega Single systems feature:

### The 1-Lamp Mega Fixture

- Built-in Barndoors
- Removable Reflector, Louver and Lamp Harness
- Slide-on Center Mount
- True Match® daylight, tungsten

### The High Output Ballast

- Flicker-free, remote lamp control
- HO/Standard switching
- Instant-on, dead quiet
- Remote operation

## ▼ Mega Single Systems



**CFX-9601**  
8ft Fixture



**CFX-7201**  
6ft Fixture



**MTP-KM**  
Kino 81 Slide-on Mount  
w/ Junior Pin (28mm)



**X07-25M**  
Extension, 25ft



**BAL-105-M120**  
Mega Ballast, 120VAC

**BAL-115-M230**  
Mega Ballast, 230VAC

## ▼ Mega Single Accessories



**MTP-BAL**  
Kino Ballast Baby Mount (16mm)



**X07-A9M**  
Mega Single to Mega Double  
Combiner



**X07-A19M**  
Mega Single to Mega 4Bank  
Combiner