

Mini-Flo®



The Mini-Flo® System, sometimes called a “car kit,” can be found most often lighting nighttime car interiors and other small areas. However, over the years the Mini-Flo’s unique lightweight and color control features have endeared it to video and broadcast lighting designers as a cool, efficient chin light for speakers at a podium or news anchors in a TV studio. The Mini-Flo is available with single ballasts, plus a choice of 9” or 12” fixture and lamp sizes. Take a look at our kits and a la carte selections below.

▼ Photometrics

| Fixture | FC | 24" | 11" | 6" | 4" |
|--------------|------|-----|------|----|----|
| Mini-Flo 12" | 79 | 24 | 11 | 6 | 4 |
| | Feet | 1 | 2 | 3 | 4 |
| Mini-Flo 9" | 85 | 23 | 10.5 | 6 | 4 |
| | Feet | 1 | 2 | 3 | 4 |

| Fixture | LUX | 388 | 170 | 98 | 63 |
|--------------|--------|------|-----|------|----|
| Mini-Flo 12" | 1227 | 388 | 170 | 98 | 63 |
| | Meters | 0.25 | 0.5 | 0.75 | 1 |
| Mini-Flo 9" | 1292 | 368 | 171 | 97 | 62 |
| | Meters | 0.25 | 0.5 | 0.75 | 1 |

▼ Fixture Specifications

| Fixture | Lamp | Lamp Type | Dimensions | Weight w/ Lamp |
|--------------|------|-----------|------------------------------------|----------------|
| Mini-Flo 12" | 1 | F8/T5 | 14 x 2.5 x 3" (35.5 x 6.5 x 7.5cm) | 0.5 lb (0.2kg) |
| Mini-Flo 9" | 1 | F6/T5 | 11 x 2.5 x 3" (28 x 6.5 x 7.5cm) | 0.4 lb (0.2kg) |

▼ Ballast Specifications

| Ballast | Input Voltage | Output Frequency | Dimming | Lamps | Amperage | Dimensions | Weight |
|----------|---------------|------------------|----------|-------|--------------------|------------------------------------|-------------------|
| Mini-Flo | 12VDC | 25kHz | 100%~15% | 1 | F8/0.9A F6/0.8A | 4.5 x 3.5 x 2" (11.5 x 9 x 5cm) | 0.8 lb (0.4kg) |

▼ Details



▼ Mini-Flo Kits



KIT-139X/12

Mini-Flo Kit 12" Universal (2x BAL-139X)

| Contents | Dimensions |
|----------------------------------|----------------------|
| 2 12VDC Mini-Flo Ballast | 21.5 x 8 x 17" |
| 2 2.4 Amp Universal Power Supply | (54.5 x 20.5 x 43cm) |
| 2 12" Fixture | Weight |
| 2 Extension, 12ft | 15 lb (6.8kg) |
| 2 Mount | |
| 1 Flex Arm, 6ft | |
| 1 Alligator Clip Adapter XLR | |
| 1 Car Adapter XLR | |
| 1 Splitter XLR | |
| 1 Travel Case | |



KIT-139X/09

Mini-Flo Kit 9" Universal (2x BAL-139X)

| Contents | Dimensions |
|----------------------------------|----------------------|
| 2 12VDC Mini-Flo Ballast | 21.5 x 8 x 17" |
| 2 2.4 Amp Universal Power Supply | (54.5 x 20.5 x 43cm) |
| 2 9" Fixture | Weight |
| 2 Extension, 12ft | 15 lb (6.8kg) |
| 2 Mount | |
| 1 Flex Arm, 6ft | |
| 1 Alligator Clip Adapter XLR | |
| 1 Car Adapter XLR | |
| 1 Splitter XLR | |
| 1 Travel Case | |

▼ Mini-Flo Kit Components/ Lamps

| | | | |
|--|--|--|---|
| | CFX-091 9" Fixture | | PWC-CX DC Car Adapter XLR, 6ft |
| | CFX-1201 12" Fixture | | PWC-X42 Splitter XLR |
| | X02-12S Extension, 12ft | | PWS-1524X Power Supply 2.4A, 100-250VAC/12VDC 4-Pin XLR |
| | BAL-139X Mini-Flo Ballast, 12VDC | | KAS-MF Mini-Flo Kit Travel Case |
| | MTP-MM Flex Arm Mount | | 092-K32 9" Kino KF32 |
| | MTP-MW6 Flex Arm, 6ft Coil | | 122-K32 12" Kino KF32 |
| | PWC-AX DC Alligator Adapter XLR, 12ft | | 092-K55 9" Kino KF55 |
| | | | 122-K55 12" Kino KF55 |