Celeb 400/400Q & 401/401Q Power Supply Repair Kit

(Part # PRT-PWS-CE4)

ITEM#	QTY	PART	DESCRIPTION	PART NO.
1	3		SCREW M3 10MM PAN PHIL SS	2020134
2	1		PWS-SL-24V/240W- 100/240VAC-3"X5"	1180065
3	1		CELEB SL PWS ADAPTER PLATE	5220100
4	1		CT-SL156- HOUSING-6PIN POLAR-LATCH	1270143
5	3		NUT M3 NYLOCK	2000027

The PRT-PWS-CE4 repair kit is used as a replacement for the #4010046 power supply used in all Celeb models 400/400Q and 401/401Q. For latest warranty information, see Kino Flo website **www.KinoFlo.com**



Power Supply Removal and Replacement

Celeb 400Q (CEL-400Q-120U) is shown for illustration purposes.




1) Remove ten (10) cover screws.



- 2) Remove power supply:
 - Remove AC input connector (A).
 - Then, remove output connector (B).
 - Next, remove four (4) screws (C).



- 3) Power supply adapter plate:
 - Place plate with single stud in upper right hand corner.




- 4) Install power supply on plate:
 - Place power supply with larger slot in upper right hand corner over studs.
 - Install three (3) nuts from kit on studs (arrows).

Celeb 400Q (CEL-400Q-120U) is shown for illustration purposes.



- 5) Replace output connector:
 - Depress tab and remove wires (D).
 - Then, lift tabs, each wire (E).
 - Next, insert wires in new connector from kit (F).



- 6) Install power supply and adapter plate:
 - Install output connector (H).
 - Then, install AC input connector (G).
 - Next, install three (3) screws from kit (arrows).



7) Re-install ten (10) cover screws.

For latest Warranty information and Certifications, see Kino Flo website at www.KinoFlo.com.

Environmental: Disposal of Old Electrical & Electronic Equipment.



This symbol on the product or on its packaging indicates that this product shall not be treated as household waste. This product is made of recyclable materials and should be disposed of in accordance with governmental regulations.

Kino Flo Inc. 2840 N. Hollywood Way, Burbank, CA 91505, USA Tel: 818 767-6528 website: www.KinoFlo.com