

Single



▼ Photometrics

| | FC | Feet | | | | | 12 |
|-------------------|-----|------|-----|------|----|----|----|
| | | 2 | 4 | 6 | 8 | 10 | |
| 4ft Single | 171 | 56 | 27 | 15.5 | 10 | 7 | |
| | 2 | 4 | 6 | 8 | 10 | 12 | |
| 2ft Single | 62 | 17 | 7.5 | 4.5 | 3 | 2 | |
| | 2 | 4 | 6 | 8 | 10 | 12 | |

| | LUX | Meters | | | | | 3 |
|-------------------|------|--------|-----|-----|-----|-----|---|
| | | 0.5 | 1 | 1.5 | 2 | 2.5 | |
| 4ft Single | 2379 | 817 | 409 | 239 | 155 | 109 | |
| | 0.5 | 1 | 1.5 | 2 | 2.5 | 3 | |
| 2ft Single | 969 | 262 | 125 | 71 | 45 | 32 | |
| | 0.5 | 1 | 1.5 | 2 | 2.5 | 3 | |

▼ Fixture Specifications

| Fixture | Lamp | Lamp Type | Dimensions | Weight w/ Lamp |
|-------------------|------|-----------|--|-------------------|
| 4ft Single | 1 | F75/T12 | 52 x 4.5 x 3.5" w/ 3.5" barndoors (132 x 11.5 x 9cm w/ 9cm barndoors) | 4.3 lb (1.9kg) |
| 2ft Single | 1 | F40/T12 | 27 x 4.5 x 3.5" w/ 3.5" barndoors (69 x 11.5 x 9cm w/ 9cm barndoors) | 2.7 lb (1.2kg) |

▼ Ballast Specifications

| Ballast | Input Voltage | Output Frequency | Amperage | Lamp Switch | Output Switch | Dimensions | Weight |
|----------------------|-------------------|------------------|---------------------------------|-------------|---------------|---------------------------------------|-------------------|
| Single Select | 120VAC 50/60Hz | 25kHz | F75/1.3A, F40/0.9A, F30/0.7A | 1-Off | 2ft-4ft | 11 x 2.5 x 2.5" (28 x 6.5 x 6.5cm) | 2 lb (0.9kg) |
| Single Select | 230VAC 50/60Hz | 25kHz | F75/0.8A, F40/0.6A, F30/0.5A | 1-Off | 2ft-4ft | 10.5 x 4 x 3" (26.5 x 10 x 7.6cm) | 2.6 lb (1.2kg) |

▼ Details



The Single portable lighting system comes in a slender package but delivers ample light for challenging spaces such as set practicals or auto interiors. Single systems feature:

The 1-Lamp Fixture

- Built-in Barndoors
- Removable Lamp Harness, Reflector and Louver
- Twist-on, locking Center Mount
- True Match® daylight and tungsten lamps

The High Output Ballast

- HO/Standard switching
- Flicker-free, remote operation
- Instant-on, dead quiet

▼ Single Systems



▼ Single Accessories

