

**CHANNEL FUNCTION**

<b>Channel</b>	
BASE ADDRESS	DIMMING
BASE ADDRESS + 1	CCT

**CHANNEL 1**

DIMMING %		DMX		DMX %	
0	6	0	20	0.0%	7.8%
6.4	100	21	255	8.2%	100.0%

**CHANNEL 2**

Kelvin (CCT)		DMX		DMX %	
2700	3030	0	22	0.0%	8.6%
3045	3171	23	32	9.0%	12.5%
3185	4400	33	114	12.9%	44.7%
4415	4471	115	119	45.1%	46.7%
4485	5400	120	181	47.1%	71.0%
5415	5471	182	186	71.4%	72.9%
5485	6415	187	249	73.3%	97.6%
6430	6500	250	255	98.0%	100.0%